

SmartOnline 208/240, 230V 16kVA 14.4kW Double-Conversion UPS, N+1, 12U Rack/Tower, Extended Run, SNMPWEBCARD Option, USB, DB9, Bypass Switch, C19

MODEL NUMBER: **SU16KRTG**



Description

Tripp Lite SU16KRTG 16,000VA / 16kVA / 14,400 watt online, double-conversion UPS system offers complete power protection for critical server, network and telecommunications equipment in a 12U rack/tower configuration. This system delivers complete N+1 redundancy when used at loads up to 8kVA, and non-redundant operation at loads between 8 and 16kVA. Fault-tolerant auto-bypass prevents unexpected service interruptions during UPS overload or internal fault conditions. Included parallel PDU with manual bypass switching enables hot-swappable replacement of all major UPS system components in both N+1 and combined operating modes. Enhanced availability, fault tolerance and simple hot-swap replacement options make this UPS ideal for advanced networking applications in data centers, computer rooms, network closets and rugged industrial locations.

Features

- Tripp Lite SU16KRTG 16kVA, 16,000VA / 14,400 watt on-line, double-conversion UPS system in 12U total rack/tower configuration
- Unique configuration offers 16kVA non-redundant operation and automatic N+1 redundancy at load levels of 8kVA and under
- Included Parallel PDU with manual bypass switch enables hot-swap replacement power modules at any supported load level
- Hardwire input; 8 C19 outlets
- Maintains full-time sine wave output within 2% of selectable 200/208/220/230/240V nominal
- Supports 50/60Hz operation for worldwide frequency compatibility
- Expandable runtime with optional external battery packs
- Some external battery configurations require the use of Tripp Lite's External Battery Configuration Software(see manual)
- Battery independent restart
- Intelligent battery management system with temperature-compensated charging extends battery life
- Highly efficient economy mode option
- Optional [SNMPWEBCARD](#), [RELAYIOCARD](#) and [RELAYIOMINI](#) interface modules available([RELAYIOMINI](#) requires removal of USB interface module)

Highlights

- 16kVA / 16,000VA / 14,400W on-line double-conversion UPS, 0.9 power factor
- 200/208/220/230/240V 50/60Hz output, 96% Efficient Economy-mode option
- Hot-swap power & battery modules, N+1 fault tolerance at loads up to 8kVA
- USB, RS232, EPO ports, Support for SNMP/WEB & other card options
- Front panel LEDs with detailed LCD monitoring and control screen
- Expandable runtime with optional external battery packs
- Hardwire input (3 wire), C19 outlets

Package Includes

- Two [SU8000RT3UPM](#) UPS power modules
- Two [BP240V10RT3U](#) battery packs
- [SUPDMB20KIEC](#) Parallel PDU with Bypass switch
- 4-post rackmount installation rails
- PowerAlert software and cabling



- Applications utilizing the optional network communications card require two [SNMPWEBCARD](#) accessories(install one per included power module)
- HID-compliant USB interface
- Includes Free PowerAlert monitoring software; PowerAlert LOCAL, PowerAlert NSA and PowerAlert NMS for monitoring up to 250 SNMP-enabled UPS, PDU and other networking devices
- Optional [2POSTRMKITHD](#) supports installation in 2 post 19 inch racks(4 required)
- Optional [2-9U STAND](#) supports upright tower placement(2 required)
- Supports Emergency Power Off(EPO) via built-in interface
- Front panel LEDs and LCD readout with scroll controls
- LED / LCD display panel rotates for viewing in rackmount or tower configurations
- External battery packs are field replaceable and hot swappable
- Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz(no de-rating)

Specifications

| OUTPUT | |
|---|--|
| Output Volt Amp Capacity (VA) | 16000 |
| Output kVA Capacity (kVA) | 16 |
| Output Watt Capacity (Watts) | 14400 |
| Output kW Capacity (kW) | 14.4 |
| Output Capacity Details | Supports up to 105% load continuously in double conversion mode, 106 to 125% for 1 minute, 126% to 150% for 30 seconds; Loads over 150% trigger immediate bypass mode operation to support loads directly from mains power; Double conversion mode is automatically restored as load levels are reduced to 95% or less |
| Power Factor | 0.9 |
| Crest Factor | 3:1 |
| Nominal Output Voltage(s) Supported | 200V; 208V; 220V; 230V; 240V |
| Nominal Voltage Details | Voltage selection via front panel LCD interface |
| Frequency Compatibility | 50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion |
| Frequency Compatibility Details | Output frequency matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz (no de-rating) |
| Output Voltage Regulation (Line Mode) | +/- 2% |
| Output Voltage Regulation (Economy Line Mode) | +/- 10% |
| Output Voltage Regulation (Battery Mode) | +/- 2% |
| Output Receptacles | (8) C19 |
| Output Circuit Breakers | 8 20A breakers protect one C19 outlet each |
| Output AC Waveform (AC Mode) | Pure Sine wave |
| Output AC Waveform (Battery Mode) | Pure Sine wave |



| INPUT | |
|--|---|
| Rated input current (Maximum Load) | 92A (200V), 88.4A (208V), 83.6A (220V), 80A (230V), 76.6A (240V) |
| Nominal Input Voltage(s) Supported | 200V AC; 208V AC; 220V AC; 230V AC; 240V AC |
| UPS Input Connection Type | Hardwire |
| UPS Input Connection Description | Hardwire input supports North American 208/240V input (L1, L2, G) and International 230/220/240V input (L, N, PE) |
| Recommended Electrical Service | 100A @ 200V-240V (L, N, PE), or 100A @ 200V, 208V, or 240V (L1, L2, G) |
| Voltage Compatibility (VAC) | 200; 208; 230; 240; 220 |
| Input Phase | Single-Phase |
| BATTERY | |
| Full Load Runtime (min.) | 5.5 minutes (14,400 watts) |
| Half Load Runtime (min.) | 13.5 minutes (7200 watts) |
| Expandable Battery Runtime | Runtime is expandable with external battery packs |
| External Battery Pack Compatibility | BP240V10RT3U ; BP240V557C-1PH ; BP240V787C-1PH ; BP240V1037C-1PH ; BP240V1407C-1PH |
| Expandable Runtime Description | For best results, add external batteries in multiples of two so that both included 8kVA power modules have an equal number and type of connected battery packs |
| DC System Voltage (VDC) | 240 |
| Battery Recharge Rate (Included Batteries) | Less than 6 hours from 10% to 90% (typical, full load discharge) |
| Battery Replacement Description | Hot-swappable, user replaceable external battery packs |
| Expandable Runtime | Yes |
| VOLTAGE REGULATION | |
| Voltage Regulation Description | 2% output voltage regulation in standard online, double-conversion mode |
| Overvoltage Correction | Corrects overvoltages up to 300V |
| Undervoltage Correction | Corrects undervoltages as low as 100V |
| USER INTERFACE, ALERTS & CONTROLS | |
| Front Panel LCD Display | Selectable LCD display with scroll and selection buttons enables UPS control and detailed monitoring options; LED/LCD panel rotates for viewing in rack/tower formats; LCD Display supports ENGLISH, FRENCH, GERMAN, ITALIAN, SPANISH and PORTUGUESE (see manual) |
| Switches | 2 Switches control off/on power status and alarm-cancel/self-test operation; 2 additional switches support set and execute scrolling LCD functions; bundled PDU includes bypass switch to enable hot-swap UPS power module replacement |
| Alarm Cancel Operation | Alarm cancel switch |
| Audible Alarm | Unique audible alarms for all major UPS, environmental and power conditions (see manual) |
| LED Indicators | 6 LEDs indicate line power, online mode, economy/bypass mode, on-battery, charger and AC output status; LCD screen offers additional information and control options |



| SURGE / NOISE SUPPRESSION | |
|---|--|
| UPS AC Suppression Response Time | Instantaneous |
| EMI / RFI AC Noise Suppression | Yes |
| PHYSICAL | |
| Included Mounting Accessory Description | 4 sets of adjustable 4 post rack rails included (one for each included 3U module) |
| Installation Form Factors Supported with Optional Accessories | 2 post rackmount(2POSTRMKITHD); Tower(2-9USTAND) |
| Optional Mounting Accessory Notes | Qty 4 2POSTRMKITHD required; Qty 2 2-9USTAND required |
| Primary Form Factor | Rackmount |
| UPS Power Module Dimensions (hwd, in.) | 5.14 x 17.5 x 25.82 |
| UPS Power Module Dimensions (hwd, cm) | 13.1 x 44.5 x 65.6 |
| Rack Height (U Spaces) | 12 |
| Maximum Device Depth (in.) | 32.5 |
| Maximum Device Depth (cm) | 82.6 |
| UPS Power Module Weight (lbs.) | 43 |
| UPS Power Module Weight (kg) | 19.5 |
| UPS Dimensions Details | Includes 2 SU8000RT3UPM UPS/Power modules and 2 BP240V10RT3U Battery packs; Listed weights and dimensions for UPS/Power module and Included battery pack each refer to a single unit |
| Included Battery Pack Dimensions (hwd / in.) | 5.25 x 17.5 x 25 |
| Included Battery Pack Dimensions (hwd / cm) | 13.3 x 44.5 x 63.5 |
| Included Battery Pack Weight (lbs.) | 158.7 |
| Included Battery Pack Weight (kg) | 72 |
| UPS Shipping Dimensions (hwd / in.) | 36 x 40.25 x 51 |
| UPS Shipping Dimensions (hwd / cm) | 91.4 x 102.2 x 129.5 |
| Shipping Weight (lbs.) | 600 |
| Shipping Weight (kg) | 272.4 |
| Cooling Method | Fans |
| UPS Housing Material | Steel |
| ENVIRONMENTAL | |
| Operating Temperature Range | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius. |



| | |
|---|--|
| Storage Temperature Range | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius. |
| Relative Humidity | 0 to 95%, non-condensing |
| AC Mode BTU / Hr. (Full Load) | 5456 |
| AC Economy Mode BTU / Hr. (Full Load) | 2046 |
| AC Mode Efficiency Rating (100% Load) | 90% |
| AC Economy Mode Efficiency Rating (100% Load) | 96% |
| Operating Elevation (ft.) | 0-3000m (0 to 10,000 ft.) |
| Audible Noise | 60 dBA at front side 1 meter |
| Operating Elevation (m) | 0-3000 m |
| COMMUNICATIONS | |
| Communications Interface | USB (HID enabled); DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface |
| Network Monitoring Port Description | Applications utilizing the optional network communications card require two SNMPWEBCARD accessories (install one per included power module); Additional contact closure support with optional RELAYIOCARD and RELAYIOMINI interface cards; RELAYIOMINI installation requires removal of panel containing USB ports |
| PowerAlert Software | Included |
| Communications Cable | USB, DB9 serial and EPO cables included |
| WatchDog Compatibility | Supports Watchdog application, OS and hard-reboot restart options for remote applications |
| LINE / BATTERY TRANSFER | |
| Transfer Time | No transfer time (0 ms.) in online, double-conversion mode |
| Transfer Time (Economy Mode) | 8 milliseconds typical power failure response in optional economy mode |
| Low Voltage Transfer to Battery Power (Setpoint) | 100V |
| High Voltage Transfer to Battery Power (Setpoint) | 300V |
| SPECIAL FEATURES | |
| Cold Start (Startup in Battery Mode During a Power Failure) | Cold-start operation supported |
| Economy Mode Operation | Optional economy mode enables high efficiency bypass operation with a maximum output voltage variation of +/-10%. Double conversion mode is automatically restored as mains voltage varies beyond +/-10% with less than 1 millisecond transfer time between modes. |
| High Availability UPS Features | Automatic inverter bypass; Hot swappable batteries; Hot swappable UPS power module; Manual bypass switch |
| Green Energy-Saving Features | High efficiency economy mode operation; Support for daily startup and shutoff; Schedulable daily hours of economy mode operation |
| CERTIFICATIONS | |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| | |
|-------------------------------------|--|
| UPS Certifications | Tested to UL1778 (USA); Tested to CSA (Canada); CE; Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances) |
| UPS Certification Details | IEC 61000-4-5 1995 B Surge Immunity |
| WARRANTY | |
| Product Warranty Period (Worldwide) | 2-year limited warranty |

© 2015 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<http://www.tripplite.com/products/product-certification-agencies>