

Please see below under Resources/Product Literature for the Power Cord Selector Worksheet for both input and output power cord selection.

Isolator Series Dual-Voltage 115/230V 300W 60601-1 Medical-Grade Isolation Transformer, C14 Inlet, 4 C13 Outlets

MODEL NUMBER: IS300HGDV



Description

The IS300HGDV Isolator® Series Dual-Voltage 115/230V 300W 50/60Hz Medical-Grade™ Transformer with full CAN/ES/IEC/EN 60601-1 listing is ideal for protecting sensitive electronic equipment in patient-care vicinities. It can be configured for either step-up voltage, step-down voltage or pass-through voltage operation. Along with line isolation and continuous EMI/RFI line noise filtering, its surge protection rating of 240 joules suppresses excess voltage to prevent it from damaging connected equipment.

An internal low-impedance isolation transformer component offers 100% isolation from the input mains AC line. Faraday shield reduces the cumulative leakage current of the IS300HGDV and connected equipment to levels less than 50 microamps, while removing utility switching transients and harmonics generated by other on-site loads and reducing the impact of utility or lightning related surge conditions.

Transformer filtering provides continuous common-mode noise rejection with no wearable parts. The IS300HGDV reduces 6000V IEEE 587 Category A and B ring wave and combination wave test surges to only 0.5V common mode.

Components connect to four C13 outlets with fuse overload protection and a lighted on/off switch. The rugged all-metal unit housing ships ready for placement in any industrial, medical, office, network or audio/video environment. Requires a C14-to-C13 AC input cord (sold separately).

Features

Full CAN/ES/IEC/EN 60601-1 Medical-Grade Listing with C14 Inlet and 4 C13 Outlets

- Ideal for protecting sensitive electronic equipment in patient-care vicinities
- Reduces cumulative leakage current of Isolator and connected equipment to levels less than 50 μ A

Highlights

- Protects sensitive equipment from EMI/RFI line noise and surges
- Cumulative leakage current less than 50 μ A
- Automatically shuts down all outlets in case of overload
- Offers complete isolation from input AC mains power
- Ideal for use in any industrial, network or medical environment

Package Includes

- IS300HGDV Isolator Series Dual-Voltage 115/230V 300W 60601-1 Medical-Grade Isolation Transformer
- (2) Fuse sets (115V and 230V operation)
- Input/output cable selector data sheet
- Owner's manual



- Inexpensive alternative to dedicated circuits and site electrical upgrades
- Rugged all-metal housing designed to withstand frequent use in busy environments
- C14-to-C13 AC input cord required (sold separately)

Selectable 115/230V Input/Output Voltage Suitable for Most Applications

- Step-up, step-down or pass-through voltage operation (input frequency always equals output frequency)
- Internal low-impedance toroidal isolation transformer with Faraday shield offers 100% isolation from mains AC power line
- Automatically shuts down all outlets in case of overload
- Ships ready for placement in any industrial, medical, office, network or audio/video environment

Protects Connected Equipment from Dangerous Spikes, Surges and Line Noise

- Line isolation, continuous noise filtering and 240 joules of AC surge protection
- Removes EMI/RFI noise, utility switching transients, load-generated harmonics and ground loops
- Floating AC output prevents noise coupling from noisy ground circuits
- Reduces 6000V IEEE 587 Category A and B ring wave and combination wave test surges to only 0.5V common mode

Specifications

MODEL TEXT	
What Does This Product Do?	Transformer with full CAN/ES/IEC/EN 60601-1 listing offers line isolation, step-up and step-down capabilities, and continuous noise filtering in protecting medical electronic equipment used in patient-care vicinities.
OVERVIEW	
Nominal Voltage / Frequency	115/230 VAC 50/60 HZ (Voltage Selected by Input Power Module Fuse Installation)
Over Current Protection	2X 3.15A @ 115V and 2X 1.6A at 230V (Both Fuses included with Product as Accesories)
VA / Watt Capacity	300
Transformer Type	Medical Grade, Low Impedence Toroid- Line Isolation (Pass Through or Step UP or Step Down)
OUTPUT	
Output Voltage Regulation (Line Mode)	5.2%
Output Receptacles	IEC320- C13
Output (VA)	300
Output (Watts)	300
Output Nominal Voltage	115V/230V (Selected by Output Switch) Can also be step up or step down, Selected when Installing Fuses.
Outlet Details	Qty 4 Receptacles



INPUT	
Nominal Input Voltage Description	115/230 VAC (Selected by Input Power Module Fuse Installation) Operating Input Voltage Range 100-125Vac or 200-250VAC
Input Frequency	50/60HZ
Maximum Surge Amps	70A
Input Current	3.15A @ 115V / 1.6A @ 230V
THDi	Less than 1%
Power Input Receptacle	IEC-320-C14
SURGE / NOISE SUPPRESSION	
AC Suppression Joule Rating	240
IEEE587 Cat. A Ringwave Let-Through	Reduced to 0.5v Common Mode
Noise Suppression Rating	35-65db
ISOLATION	
Output Isolation Transformer	Toroid with AC output Floating with Respect to Earth Ground. POAG and Earth Ground Studs.
Leakage Current	Max AC Leakage Current 50 (uA)
PHYSICAL	
Shipping Dimensions (hwd / in.)	8.27 x 9.84 x 12.8
Shipping Dimensions (hwd / cm)	21.01 x 24.99 x 32.51
Shipping Weight (lbs.)	13.62
Shipping Weight (kg)	6.18
Unit Dimensions (hwd / in.)	4.33 x 5.91 x 7.87
Unit Dimensions (hwd / cm)	11 x 15 x 20
Unit Weight (lbs.)	12.35
Unit Weight (kg)	5.60
Cooling Method	Convection
Material of Construction	Sheet Metal Cabinet
Color	White
ENVIRONMENTAL	
Operating Temperature Range	0 C-40 C(32F to 104F), Intended Application is in a controlled environment at approx. 25 C.
Storage Temperature Range	-15 C to 50 C (5F to 122F)
Operating Elevation (m)	0-3000M (0-10,000 Ft)
Operating Humidity Range	5% to 95% RH (Non-Condensing)



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

CERTIFICATIONS	
Certifications	Tested to ANSI/AAMI ES60601-1:2005+A2+A1, IEC60601-1 3RD EDITION +A1, cAN/CSA-C22.2 NO. 60601-1:14, CE, NOM
OPERATION	
System Type Selections	Input Voltage equals Output Voltage OR 120V input equals 230V output OR 230V Input equals 120V output - (Selectable when installing Fuses) Input Frequency always equals Output Frequency

© 2018 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>